MICROSTRIP LINE, METHOD FOR FABRICATING THE SAME, INDUCTOR ELEMENT, AND RF SEMICONDUCDTOR DEVICE

BACKGROUND OF THE INVENTION

5   The present invention relates to a microstrip line, to a method for fabricating the same, to an inductor element, and to an RF semiconductor device.

As the number of users of radio communication systems including mobile phones has increased year by year, size and
10   cost reduction has been required increasingly of mobile terminal equipment used in the radio communication systems. An RF device which is a primary component of the mobile terminal equipment has been reduced in cost by forming it into a so-called MMIC (Monolithic Microwave IC) in which an
15   active element and a passive element are formed integrally in a substrate, instead of forming it into a multichip IC in which the active and elements are integrated separately in the substrate as has been practiced conventionally.

FIG. **15** shows a conventional RF circuit. FIG. **16** shows
20   a plan configuration of an RF semiconductor device in which the RF circuit shown in FIG. **15** is implemented in a substrate. In FIG. **16**, the same components as shown in FIG. **15** are designated by the same reference numerals.

As can be seen from FIGS. **15** and **16**, each of passive
25   elements including spiral inductors **302** and **303** disposed

1

between an input terminal 311 and an amplifying FET 301, spiral inductors 304 and 305 disposed between the drain of the FET 301 and an output terminal 312, and a dc blocking capacitance 306 occupies an area larger than occupied by the amplifying FET 301 which is an active element.

To further reduce the RF semiconductor device in cost, it is necessary to reduce the passive elements in size and thereby increase chip yield per slice (wafer). Chip area has been reduced conventionally by using a strontium titanium oxide (STO), which is a high dielectric material, as a dielectric material composing a dc blocking capacitance or by-pass capacitance and thereby reducing the area of the capacitance (GaAs IC symposium 1998).

On the other hand, Japanese Unexamined Patent Publications Nos. HEI 8-116028 and HEI 9-148525 disclose technology for reducing the size of an inductor element by using STO as a dielectric material composing a microstrip line and thereby reducing the wavelength of a signal electromagnetic wave.

However, the conventional microstrip line has the problem of degrading the characteristics of the MMIC since, if the width of the line is reduced such that the characteristic impedance of the line or the inductance of the inductor is increased, the cross-sectional area of the line is reduced and a conductor loss is increased accordingly.

2

To increase the impedance of the microstrip line disclosed in Japanese Unexamined Patent Publication No. HEI 8-116028 or HEI 9-148525, in particular, it is necessary to reduce the width of the line to 0.5 μm or less since a high dielectric material is used as the dielectric material composing the microstrip line, which presents an obstacle to the practical use thereof. This is because a dielectric thin film formed by sputtering or physical or chemical vapor deposition such as CVD is difficult to increase in thickness. In order to increase the impedance of a microstrip line, in general, it is necessary to reduce the width of the linear conductor portion, which increases a conductor loss in the linear conductor portion.

SUMMARY OF THE INVNETION

It is therefore an object of the present invention to prevent an increase in conductor loss even if the width of a microstrip line is reduced such that the impedance of the microstrip line or the inductance of an inductor element is increased and thereby solve the foregoing problem encountered by the prior art.

To attain the object, a microstrip line according to the present invention comprises: a ground conductor layer; a dielectric layer formed on the ground conductor layer; and a linear conductor layer formed on the dielectric layer to have

3

a linear configuration, the linear conductor layer having a wider portion in an upper part of a cross section thereof taken in a direction perpendicular to a direction in which the linear conductor layer extends and a narrower portion in

5 a lower part of the cross section, the narrower portion being smaller in width than the wider portion.

In the microstrip line of the present invention, an increase in conductor loss is prevented since the impedance and inductance can be increased in the part thereof closer to

10 the dielectric layer and, in addition, the upper part thereof at a distance from the dielectric layer is larger in width than the narrower portion. This allows a reduction in the size of an RC semiconductor device without degrading the operation characteristics thereof.

15 Preferably, the microstrip line of the present invention further comprises a substrate for holding the ground conductor layer, the substrate being located under the ground conductor layer and composed of a dielectric material, wherein the dielectric layer has a dielectric constant higher

20 than a dielectric constant of the substrate. In the arrangement, the wavelength of an RF signal propagating through the linear conductor is reduced so that an RF circuit is surely reduced in size.

In the microstrip line of the present invention, the

25 dielectric layer preferably contains a titanium oxide.

4

In this case, the titanium oxide is preferably a strontium titanate.

A method for fabricating a microstrip line according to the present invention comprises the steps of: forming a ground conductor layer on a substrate composed of a dielectric material; forming a dielectric layer on the ground conductor layer; forming a mask pattern having a linear opening on the dielectric layer; depositing a layer forming a linear conductor layer on the mask pattern including the opening; and patterning the linear-conductor-layer forming layer such that the linear-conductor-layer forming layer on the mask pattern has a width larger than a width of the opening.

The method for fabricating a microstrip line of the present invention forms the linear-conductor-layer forming layer such that the width of the linear-conductor-layer forming layer is larger than the width of the opening, thereby forming the linear conductor layer having the wider portion in the upper part of the cross section and the narrower portion narrower than the wider portion in the lower part of the cross section. This ensures the formation of the wider portion and the narrower portion of the linear conductor layer of the microstrip line according to the present invention.

An inductor element according to the present invention

5

comprises a microstrip line composed of a ground conductor layer, a dielectric layer formed on the ground conductor layer, and a linear conductor layer formed on the dielectric layer to have a linear configuration, the linear conductor

5 layer being formed in a spiral configuration in a plane parallel to the dielectric layer and having a wider portion in an upper part of a cross section thereof taken in a direction perpendicular to a direction in which the linear conductor layer extends and a narrower portion in a lower

10 part of the cross section, the narrower portion being smaller in width than the wider portion.

An RF semiconductor device according to the present invention comprises: an active element formed in a substrate; and a microstrip line formed on the substrate to propagate

15 input/output signals to and from the active element, the microstrip line being composed of a ground conductor layer formed on the substrate, a dielectric layer formed on the ground conductor layer, and a linear conductor layer formed on the dielectric layer to have a linear configuration, the

20 linear conductor layer having a wider portion in an upper part of a cross section thereof taken in a direction perpendicular to a direction in which the linear conductor layer extends and a narrower portion in a lower part of the cross section, the narrower portion being smaller in width

25 than the wider portion.

6

In the RF semiconductor device of the present invention, the wavelength of an RF signal propagating through the linear conductor becomes shorter when a high dielectric material is used in the dielectric layer thereof. This ensures a

5   reduction in the size of the RF semiconductor device.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a structural cross-sectional view showing a microstrip line according to a first embodiment of the

10   present invention;

FIGS. 2A to 2C are structural cross-sectional views illustrating the individual process steps of a method for fabricating the microstrip line according to the first embodiment;

15   FIGS. 3A and 3B are structural cross-sectional views illustrating the individual process steps of the method for fabricating the microstrip line according to the first embodiment;

FIG. 4 is a structural cross-sectional view of a

20   microstrip line according to a second embodiment of the present invention;

FIGS. 5A to 5C are structural cross-sectional views illustrating the individual process steps of a method for fabricating the microstrip line according to the second

25   embodiment;

FIGS. **6A** and **6B** are structural cross-sectional views illustrating the individual process steps of the method for fabricating the microstrip line according to the second embodiment;

5   FIG. **7** is a circuit diagram of an RF semiconductor device according to a third embodiment of the present invention;

FIG. **8** is a Smith chart for illustrating input/output impedance matching in the RF semiconductor device according to the third embodiment;

10   FIG. **9** is a partial perspective view showing the vicinity of an input matching circuit in the RF semiconductor device according to the third embodiment;

FIGS. **10A** to **10D** are structural cross-sectional views illustrating a method for fabricating a microstrip line

15   according to the third embodiment;

FIGS. **11A** to **11D** are structural cross-sectional views illustrating the method for fabricating the microstrip line according to the third embodiment;

20   FIGS. **12A** to **12D** are structural cross-sectional views illustrating the method for fabricating the microstrip line according to the third embodiment;

FIGS. **13A** to **13C** are structural cross-sectional views illustrating the method for fabricating the microstrip line

25   according to the third embodiment;

8

FIGS. 14A to 14C are structural cross-sectional views illustrating the method for fabricating the microstrip line according to the third embodiment;

FIG. 15 is a circuit diagram of a conventional RF semiconductor device; and

FIG. 16 is a plan view of the conventional RF semiconductor device formed into an MMIC.

DETAILED DESCRIPTION OF THE INVENTION

EMBODIMENT 1

A first embodiment of the present invention will be described with reference to the drawings.

FIG. 1 shows a cross-sectional structure of a microstrip line according to the first embodiment. As shown in FIG. 1, a microstrip line composed of a ground electrode 12 as a ground conductor layer, a dielectric layer 13 composed of a strontium titanate oxide ($SrTiO_3$) with a thickness of about 0.5 μm, and a linear conductor layer 14 is formed on a semi-insulating substrate 11 composed of GaAs.

The ground electrode 12 consists of: a first layer 12a composed of a multilayer structure of titanium (Ti) with a thickness of about 0.05 μm and gold (Au) with a thickness of about 0.5 μm; a second layer 12b composed of Au with a thickness of about 2.5 μm; and a third layer 12c composed of a multilayer structure of platinum (Pt) with a thickness of

9

about 0.2 μm and Ti with a thickness of about 0.02 μm, which are stacked in this order on the substrate 11.

The linear conductor layer 14 is composed of a wider portion 14b with a width of about 5 μm and a narrower
5   portion 14a with a width of about 0.5 μm which extends downwardly of the wider portion 14b. The linear conductor layer 14 is a multilevel structure composed of a plurality of materials, which consists of: a first layer 15 composed of a tungsten silicon nitride (WSiN) with a thickness of about 0.1
10 μm; a second layer 16 composed of a multilayer structure of Ti with a thickness of about 0.05 μm and Au with a thickness of about 0.5 μm; and a third layer 17 composed of Au with a thickness of about 3 μm.

The upper surface of the dielectric layer 13 and the
15 side and upper surfaces of the linear conductor layer 14 are covered with a protective insulating layer (a passivation film) 18 composed of silicon dioxide (SiO$_2$) with a thickness of about 0.5 μm.

Referring to the drawings, a description will be given
20 to a method for fabricating the microstrip line thus constituted.

FIGS. 2A to 2C and FIGS. 3A and 3B show the cross-sectional structures of the microstrip line according to the first embodiment in the individual process steps of the
25 fabrication method therefor.

10

First, as shown in FIG. **2A**, the first layer **12a** composed of the Ti/Au multilayer structure, the second layer **12b** composed of Au, and the third layer **12c** composed of the Pt/Ti multilayer structure are formed on the substrate **11** by vapor deposition, whereby the ground electrode **12** composed of the first, second, and third layers **12a**, **12b**, and **12c** is formed.

Next, as shown in FIG. **2B**, the dielectric layer **13** composed of a STO is deposited over the entire surface of the ground electrode **12** by RF sputtering for which the substrate temperature is adjusted to about 300 ℃. Subsequently, the first layer **15** of the linear conductor layer composed of WSiN is deposited by RF sputtering. Then, a first resist film **21** having a line pattern with a width of about 0.5 μm is formed and the first layer **15** is etched back to be patterned by using carbon tetrafluoride (CF_4) and using the first resist film **21** as a mask, thereby forming the narrower portion **14a**. Subsequently, sintering (heat treatment) is performed in an oxygen ambient at a temperature of about 450 ℃, which recrystallizes the dielectric layer **13** and provides uniform crystal orientation as well as a high dielectric constant.

Next, as shown in FIG. **2C**, a positive second resist film **22** is coated on the entire surface of the substrate **11** and formed by lithography into an opening pattern for exposing the first layer **15**. Then, a layer **16A** forming the

11

second layer of the linear conductor layer composed of the Ti/Au multilayer structure is deposited by vapor deposition over the entire surface of the second resist film **22** including the wall and bottom surfaces of the opening pattern.

5 Next, as shown in FIG. **3A**, a negative third resist film **23** is coated on the second-layer forming layer **16A** and formed into an opening pattern with a width of about 5 μ m by lithography such that the first layer **15** of the linear conductor layer is included therein. Subsequently, the third

10 layer **17** of the linear conductor layer composed of Au is formed on the layer **16A** forming the second layer of the linear conductor layer by plating using the third resist film **23** as a mask.

Next, as shown in FIG. **3B**, the third resist film **23** is removed and an unwanted portion of the Au layer in the upper part of the multilayer structure composing the second-layer forming layer **16A** is removed by using an etchant composed of potassium iodine (KI). Subsequently, an unwanted portion of the Ti layer in the lower part of the multilayer structure composing the second-layer forming layer **16A** is removed by

20 using hydrogen fluoride (HF), whereby the second-layer forming layer **16A** is patterned into the second layer **16** of the linear conductor layer **14**. Thereafter, the second resist film **22** is removed by using a resist remover and then the

25 protective insulating film **18** composed of a silicon dioxide

12

is deposited entirely over the dielectric layer **13** so as to cover the linear conductor layer **14**.

By the foregoing fabrication steps, there is obtained the microstrip line in a T-shaped cross-sectional configuration having the upper part composed of the wider portion **14b** and the lower part composed of the narrower portion **14a** which is narrower than the wider portion **14b**.

Instead of the second resist film **22**, a mask pattern composed of a silicon nitride may also be used. In this case, the etchant is composed of, e.g., a hot phosphoric acid.

Thus, if STO is used in the dielectric layer **13** formed between the linear conductor layer **14** and the ground electrode **12** in the microstrip line, the dielectric constant of STO is as high as 200 so that the wavelength of an electromagnetic wave propagating along the microstrip line becomes about a quarter of that of an electromagnetic wave propagating along a microstrip line using GaAs as a dielectric material. This indicates that, if STO is used in the dielectric layer **13**, the quarter wavelength ($\lambda/4$) of an electromagnetic wave which is 6 mm at a frequency of 5 GHz when GaAs is used in the dielectric layer **13** is reduced to the order of 1.5 mm. The wavelength reducing effect allows the adoption of a distributed constant circuit at 5 GHz, which has been impossible due to a chip size limit, thereby achieving a significant reduction in chip size.

13

Under the present circumstances, however, the formation of a STO film with a thickness of 0.5 μm requires two hours so that the formation of a thicker STO film is not appropriate because it further reduces throughput. To implement a microstrip line with higher impedance, therefore, a reduction in the width of the conductive material is essential. However, a mere reduction in width incurs a higher loss in the microstrip line.

The first embodiment forms the part of the linear conductor layer **14** which adjoins the dielectric layer **13** into the narrower portion **14a** and defines the impedance of the line by the narrower portion **14a**, while forming the part of the linear conductor layer **14** at a distance from the dielectric layer **13** into the wider portion **14b** and thereby restricting a conductor loss. This provides a high-impedance and low-loss line.

Although the protective insulating film **18** composed of the silicon dioxide has been filled in the space between the wider portion **14b** of the linear conductor layer **14** and the dielectric layer **13** in order to protect the strip line, it is preferred not to fill the protective insulating film **18** in terms of operation characteristics. In the case of filling the protective insulating film **18**, therefore, a low dielectric film having a relatively low dielectric constant such as an organic material composed of, e.g.,

14

benzocyclobutene, Duroid · , or a polyimide film is used preferably.

Preferably, a larger distance is provided between the dielectric layer 13 and the wider portion 14b. The arrangement suppresses the coupling capacitance between the wider portion 14b and the ground electrode 12. If the coupling capacitance is increased, the wider portion 14b greatly affects the impedance of the strip line and prevents the strip line from having higher impedance.

The microstrip line according to the first embodiment may be used appropriately to form an inductor element such as a spiral inductor element. The arrangement increases a relative coefficient determined by the ratio of the width of the linear conductor layer 14 to the distance between the linear conductor layer 14 and the ground electrode 12 so that the inductance value of the spiral inductor element is increased.

Because the relative coefficient is also applied to an inductor element having a configuration other than a spiral, the microstrip line according to the present embodiment is also effective not only in the spiral inductor element but also in inductor elements having other configurations such as a meander and a loop.

Although the first embodiment has used Au as the primary material of the linear conductor layer 14 and the

15

ground electrode **12**, the use of a material having a conductivity higher than that of Au, such as Ag or Cu, further reduces the conductor loss. Alternatively, a superconducting material may also be used as the primary

5   material of the linear conductor layer **14** and the ground electrode **12**.

Although the first embodiment has configured the microstrip line as a thin-film microstrip line (TFMS) using STO in the dielectric layer **13** thereof, a thin film composed

10   of an organic material or another dielectric material may also be used in the dielectric layer **13** of the thin-film microstrip line.

Although the first embodiment has used GaAs in the substrate **11**, an inorganic material composed of a glass

15   material such as Si or quartz or of alumina or an organic material composed of polystyrene or Teflon · may also be used instead.

It is also possible to use the linear conductor layer **14** having the cross section according to the present

20   embodiment as a signal line of a coplanar line.

EMBODIMENT 2

A second embodiment of the present invention will be described with reference to the drawings.

25   FIG. **4** shows a cross-sectional structure of a

16

microstrip line according to the second embodiment. As shown

in FIG. **4**, a ground electrode **32** as a ground conductor layer,

a dielectric layer **33** composed of a strontium titanate (STO)

with a thickness of about 0.5 μm, and a microstrip line

5 composed of a linear conductor layer **34** are formed on a semi-

insulating substrate **31** composed of GaAs.

The ground electrode **32** consists of: a first layer **32a**

composed of a multilayer structure of Ti with a thickness of

about 0.05 μm and Au with a thickness of about 0.5 μm; a

10 second layer **32b** composed of Au with a thickness of about 2.5

μm; and a third layer **32c** composed of a multilayer structure

of Pt with a thickness of about 0.2 μm and Ti with a

thickness of about 0.02 μm, which are stacked in this order

on the substrate **31**.

15 The linear conductor layer **34** is composed of a narrower

portion **34a** with a width of about 0.5 μm and a wider portion

34b with a width of about 5 μm. The linear conductor layer

34 is a multilevel structure composed of a plurality of

materials, which consists of a first layer **35** composed of

20 WSiN with a thickness of about 0.1 μm, a second layer **36**

composed of a multilayer of Ti with a thickness of about 0.05

μm and Au with a thickness of about 0.5 μm, and a third

layer **37** composed of Au with a thickness of about 3 μm.

A support insulating film **38** composed of a low

25 dielectric material such as silicon dioxide (SiO_2) with a

17

thickness of about 1 μm is filled in the space between the upper surface of the dielectric layer **33** and the narrower portion **34a** of the linear conductor layer **34**.

Referring to the drawings, a description will be given

5 to a method for fabricating the microstrip line thus constituted.

FIGS. **5A** to **5C** and FIGS. **6A** and **6B** show the cross-sectional structures of the microstrip line according to the second embodiment in the individual process steps of the

10 fabrication method therefor.

First, as shown in FIG. **5A**, the first layer **32a** composed of the Ti/Au multilayer, the second layer **32b** composed of Au, and the third layer **32c** composed of the Pt/Ti multilayer structure are deposited successively on the

15 substrate **31** by vapor deposition, whereby the ground electrode **32** composed of the first, second, and third layers **32a**, **32b**, and **32c** is formed on the substrate **31**.

Next, as shown in FIG. **5B**, the dielectric layer **33** composed of STO is deposited over the entire surface of the

20 ground electrode **32** by RF sputtering for which the substrate temperature is adjusted to about 300 ℃. Then, a first resist film **41** having a line pattern with a width of about 0.5 μm is formed on the region of the deposited dielectric layer **33** on which the narrower portion of the linear

25 conductor layer is to be formed. Subsequently, a support-

18

insulating-film forming film **38A** composed of SiO₂ is deposited entirely over the dielectric layer **33** including the first resist film **41** by, e.g., ion beam sputtering.

Next, as shown in FIG. **5C**, the narrower-portion formation region of the dielectric layer **33** is exposed by lifting off the first resist film **41**. Then, the first layer **35** of the linear conductor layer composed of WSiN is deposited by RF sputtering. Thereafter, a second resist film **42** is coated on the deposited first layer **35** and formed into a line pattern with a width of about 5 μm by lithography so as to include the narrower-portion formation region. Subsequently, the first layer **35** is etched back by using the formed second resist film **42** as a mask and using CF₄ to be formed into a pattern including the narrower portion **34a**. Thereafter, sintering is performed in an oxygen ambient at a temperature of about 450 ℃ to recrystallize the dielectric layer **33** and thereby increase the dielectric constant of the dielectric layer **33**.

Next, as shown in FIG. **6A**, a layer **36A** forming the second layer of the linear conductor layer is formed entirely over the support insulating film **38** and the first layer **35** by vapor deposition. Thereafter, a third resist film **43** is coated on the second layer forming layer **36A** and formed by lithography into an opening pattern having a width of about 5 μm and including the first layer **35** of the linear conductor

19

layer. Subsequently, the third layer **37** of the linear conductor layer composed of Au is formed by plating on the layer **36A** forming the second layer of the linear conductor layer by using the third resist film **43** as a mask.

5   Next, as shown in FIG. **6B**, the third resist film **43** is removed and an unwanted portion of the Au layer in the upper part of the multilayer structure of the second-layer forming layer **36a** is removed by using an etchant composed of KI. Subsequently, an unwanted portion of the Ti layer in the

10   lower part of the multilayer structure of the second-layer forming layer **36A** is removed by using hydrogen fluoride, whereby the second-layer forming layer **36A** is patterned into the second layer **36** of the linear conductor layer **34**.

By the foregoing fabrication steps, there is obtained

15   the microstrip line in an inverted trapezoidal cross-sectional configuration having curved hypotenuses. Depending on the thickness of the support insulating film **38**, it is also possible to provide generally straight hypotenuses instead of the curved hypotenuses.

20   If STO is used in the dielectric layer **33** formed between the linear conductor layer **34** and the ground electrode **32** in the microstrip line as in the second embodiment, the wavelength of an electromagnetic wave propagating along the microstrip line becomes about a quarter

25   of that of an electromagnetic wave propagating along a

20

microstrip line using GaAs as a dielectric material. This indicates that, if STO is used in the dielectric layer **33**, the quarter wavelength ($\lambda/4$) of an electromagnetic wave which is 6 mm at a frequency of 5 GHz when GaAs is used in

5　　the dielectric layer **33** is reduced to the order of 1.5 mm. The wavelength reducing effect allows the adoption of a distributed constant circuit at 5 GHz, which has been impossible due to a chip size limit, thereby achieving a significant reduction in chip size.

10　　　　However, the formation of a STO film with a larger thickness is not realistic, as described above. Although a reduction in the width of the conductive material is essential to implementing a microstrip line with higher impedance, a mere reduction in width incurs a higher loss in

15　　the microstrip line.

　　　　The second embodiment forms the part of the linear conductor layer **34** which adjoins the dielectric layer **33** into the narrower portion **34a** and defines the impedance of the line by the narrower portion **34a**, while forming the part of

20　　the linear conductor layer **34** at a distance from the dielectric layer **33** into the wider portion **34b** and thereby restricting a loss by the wider portion **34b**. This implements a high-impedance and low-loss line.

　　　　Although silicon dioxide has been used in the support

25　　insulating film **38** which determines the configuration of the

21

narrower portion **34a** of the linear conductor layer **34**, it is preferred not to fill such an insulating material into the space between the dielectric layer **33** and the narrower portion **34a**. To prevent the insulating material composed of

5   the silicon dioxide from being filled, the insulating material may be removed appropriately with hydrogen fluoride. In the case of filling the insulating material, a low dielectric film having a dielectric constant lower than that of the silicon dioxide composed of an organic material, such

10   as BCB, Duroid · , or a polyimide film, is used preferably. In this case, an organic material is deposited properly by CVD or like method.

Preferably, a larger distance is provided between the dielectric layer **33** and the wider portion **34b**. The

15   arrangement suppresses the coupling capacitance between the wider portion **34b** and the ground electrode **32**. If the coupling capacitance is increased, the wider portion **34b** greatly affects the impedance of the strip line and prevents the strip line from having higher impedance.

20   The microstrip line according to the second embodiment may also be used appropriately to form an inductor element such as a spiral inductor element. The arrangement increases a relative coefficient determined by the ratio of the width of the linear conductor layer **34** to the distance between the

25   linear conductor layer **34** and the ground electrode **32** so that

22

the inductance value of the spiral inductor element is increased.

Because the relative coefficient is also applied to an inductor element having a configuration other than a spiral, the microstrip line according to the present invention is also effective not only in the spiral inductor element but also in inductor elements having other configurations such as a meander, a loop, and the like.

Although the second embodiment has used Au as the primary material of the linear conductor layer **34** and the ground electrode **32**, the use of a material having a conductivity higher than that of Au, such as Ag or Cu, further reduces a conductor loss. Alternatively, a superconducting material may also be used as the primary material of the linear conductor layer **34** and the ground electrode **32**.

Although the second embodiment has configured the microstrip line as a thin-film microstrip line using STO in the dielectric layer **33** thereof, a thin-film microstrip line using a thin film composed of an organic material or another dielectric material in the dielectric layer **33** is also effective.

Although the second embodiment has used GaAs in the substrate **31**, an inorganic material composed of a glass material such as Si or quartz or of alumina or an organic

23

material composed of polystyrene or Teflon· may also be used instead.

It is also possible to use the linear conductor layer 34 having the cross section according to the present embodiment as a signal line of a coplanar line.

Wherein, explained here is the case that the narrower portion 34a and the wider portion 34b shown in FIG. 4 are integrated into the conductor layer 34. However, the same effects as in this case may be obtained in such a manner that the narrower portion 34a and the wider portion 34b are respectively made of independent conductive materials through an insulator and the conductive materials are electrically connected with each other through at least one part. The same effects can be obtained in the case of the narrower portion 14a and the wider portion 14b in FIG. 1.

In FIG. 4, when the substrate 31 has a ground potential, the substrate 31 serves as the ground electrode 32, which results in no electrode 32 required. The same can be said in the case of the ground electrode 12 in FIG. 1.

EMBODIMENT 3

A third embodiment of the present invention will be described with reference to the drawings.

FIG. 7 shows a circuit structure in an RF semiconductor device according to the third embodiment. As shown in FIG. 7,

24

an input matching circuit is connected to the input side of a FET **51** which is an RF amplifying element and an output matching circuit is connected to the output side thereof.

The input matching circuit is composed of: a dc blocking first capacitor element **54** connected in series between an RF input terminal **52** and the gate of the FET **51**; a $\lambda/4$ wavelength line (microstrip line) **55**; a first inductor element **56** which is an RF choke for bias supply; and a second capacitor element **57** for short-circuiting the RF component of the first inductor element **56**.

The output matching circuit is composed of: a dc blocking third capacitor element **58** connected in series between the drain of the FET **51** and an RF output terminal **53**; a second inductor element **59** connected in parallel to the drain; and a fourth capacitor element **60** for short-circuiting the RF component of the second inductor element **59**. The second inductor element **59** and the fourth capacitor element **60** are provided also to supply a bias signal. In the arrangement, each of the input/output impedances of the FET **51** is converted to about 50 Ω.

FIG. **8** is a Smith chart showing the conversion of the input/output impedances of the FET **51**. As shown in FIG. **8**, it is assumed that the input impedance of the FET **51** is located at the point A on the chart and the output impedance thereof is located at the point B. The input impedance is

converted to about 50 Ω by the λ/4 wavelength line **55**, while the output impedance is converted to about 50 Ω by the second inductor element **59** and the third capacitor element **58**.

FIG. **9** is a partial perspective view of the RF semiconductor device shown in FIG. **7**. It is assumed here that the microstrip line shown in the first embodiment is applied by way of example only to the input side. Accordingly, only the region **50** shown in FIG. **7**, i.e., only the components including the input matching circuit and the FET **51** are shown.

As shown in FIG. **9**, in the RF device according to the third embodiment, a ground electrode **112** and a dielectric layer **113** composed of a STO with a thickness of about 0.5 μm are formed successively on a semi-insulating substrate **111** composed of GaAs to compose the substrate of the microstrip line portion. It is to be noted that the ground electrode **112** has the same structure as shown in FIG. **1**. That is, the ground electrode **112** consists of: a first layer composed of a multilayer structure of Ti with a thickness of about 0.05 μm and Au with a thickness of about 0.5 μm; a second layer composed of Au with a thickness of about 2.5 μm; and a third layer composed of a multilayer structure of Pt with a thickness of about 0.2 μm and Ti with a thickness of about 0.02 μm, which are stacked in this order on the substrate **111**. For the sake of simplifying the drawings, a FET **151** is

26

represented as a rectangular parallelepiped.

The input side of the FET **151** is connected to one end of a meander-shaped microstrip line **155** which corresponds to the $\lambda/4$ wavelength line **55** shown in FIG. **7**.

5 The other end of the microstrip line **155** is connected to one electrode of a first MIM capacitor **154** corresponding to the first capacitor element **54** shown in FIG. **7** and using STO in a capacitor insulating film. The other electrode of the first MIM capacitor **154** is connected to an RF input

10 terminal **152** corresponding to the RF input terminal **52** shown in FIG. **7**.

The RF input terminal **152** has a ground-signal-ground (G-S-G) configuration which allows the RF characteristics of the RF device according to the present embodiment to be

15 evaluated by using a probe for RF evaluation and has a ground terminal **152a** connected to the ground electrode **112** through a via **152b**.

A connecting portion between the microstrip line **155** and the first MIM capacitor **154** is connected to one end of a

20 spiral inductor **156** corresponding to the first inductor element **56** shown in FIG. **7**. The other end of the spiral inductor **156** is connected to one electrode of a second MIM capacitor **157** corresponding to the second capacitor element **57** shown in FIG. **7** and using STO in a capacitor insulating

25 film. The other electrode of the second MIM capacitor **157** is

27

connected to a pad **121** for DC supply.

Referring to the drawings, a description will be given to a method for fabricating the RF semiconductor device thus constituted.

FIGS. **10A** to **14C** show the cross-sectional structures of the RF semiconductor device according to the third embodiment in the individual process steps. For the sake of simplicity, the description will be given to a method for forming, over the substrate **211**, a region different from the region **50** shown in FIG. **7** and including a FET formation region **1** in which a FET as an amplifying element is to be formed and a line formation region **2** in which a microstrip line is to be formed, as shown in FIG. **10A**.

First, as shown in FIG. **10A**, there is prepared a substrate obtained by forming an epitaxial layer including a heterojunction active layer (channel layer) for a FET on the semi-insulating substrate **211** composed of GaAs. The epitaxial layer is composed of, e.g., a buffer layer composed of AlGaAs or InGaAs, a graded buffer layer in which the composition gradually varies from AlAs to InAlAs with a distance from the substrate **211**, a channel layer composed of InGaAs, a barrier layer composed of InAlAs having an energy gap larger than that of the channel layer and forming a two-dimensional electron gas layer at an interface with the channel layer, and a contact layer composed of InGaAs, which

are stacked in this order on the substrate **211**.

Next, mesa etching is performed with respect to the FET formation region **1**. Subsequently, a first resist film **251** is coated on the substrate **211** and formed into a line pattern **252a** with a width of about 0.2 μm, which is for determining the gate length of the FET, in the FET formation region **1** by lithography using a phase shifting method. Thereafter, a first protective insulating film **212** composed of SiO_2 with a thickness of about 0.2 μm is deposited over the entire surface of the substrate **211** by ion beam sputtering using the first resist film **251** as a mask.

Next, as shown in FIG. **10B**, the first resist film **251** is lifted off and then a second protective insulating film **213** composed of SiN with a thickness of about 0.3 μm is formed by CVD entirely over the substrate **211** including the first protective insulating film **212**.

Next, as shown in FIG. **10C**, a layer **215A** forming the first layer of the ground electrode and composed of a multilayer structure of Ti with a thickness of about 0.05 μm and Au with a thickness of about 0.5 μm is formed over the entire surface of the second protective insulating film **213** by vapor deposition.

Next, as shown in FIG. **10D**, a second resist film **252** covering the FET formation region **1** is formed. Then, a layer **215B** forming the second layer of the ground electrode and

29

composed of Au with a thickness of about 2.5 μm is formed by plating. Subsequently, a layer **215C** forming the third layer of the ground electrode and composed of a multilayer structure of Pt with a thickness of about 0.2 μm and Ti with

5 a thickness of about 0.02 μm is formed by vapor deposition again.

Next, the second resist mask **252** is removed and the layer **215A** forming the first layer in the FET formation region **1** is removed therefrom by using a KI etchant and

10 hydrogen fluoride, whereby a ground electrode **215** composed of the first-layer forming layer **215A**, the second-layer forming layer **215B**, and the third-layer forming layer **215C** is formed in the line formation region **2**. Subsequently, a third protective insulating film **216** composed of SiN with a

15 thickness of about 0.3 μm is deposited over the entire surface of the substrate **211**.

Next, as shown in FIG. **11B**, a third resist mask **253** having an opening pattern in the line formation region **2** is formed on the third protective insulating film **216** by

20 lithography. Subsequently, RIE etching is performed with respect to the third protective insulating film **216** by using the third resist film **253** as a mask, thereby exposing the ground electrode **215**.

Next, as shown in FIG. **11C**, the third resist film **253**

25 is removed and then a dielectric layer **217** composed of STO

30

with a thickness of about 0.5 μm is deposited entirely over the substrate 211 including the line formation region 2 by RF sputtering for which the substrate temperature is adjusted to about 300 ℃.

5   Next, as shown in FIG. 11D, the portion of the dielectric layer 217 included in the FET formation region 1 is removed by a milling method using a fourth resist mask 254 covering the line formation region 2 of the dielectric layer 217.

10   Next, as shown in FIG. 12A, the fourth resist mask 254 is removed and then a layer 218A forming the first layer of the linear conductor layer and composed of WSiN with a thickness of about 0.1 μm is deposited over the entire surface of the substrate 211 by RF sputtering. Thereafter, the dielectric layer 217 is recrystallized by performing

15   sintering in an oxygen ambient at a temperature of about 450 ℃.

    Next, as shown in FIG. 12B, a fifth resist film 255 having a line pattern with a width of about 0.5 μm for

20   forming the narrower portion of the linear conductor layer is formed on the first-layer forming layer 218A. Subsequently, RIE etching is performed with respect to the first-layer forming layer 218A by using CF_4 and SF_6 as an etchant and using the fifth resist film 255 as a mask, thereby forming

25   the first layer 218 of the linear conductor layer composed of

31

the first-layer forming layer **218A** in the line formation region **2**.

Next, as shown in FIG. **12C**, a sixth resist film **256** having an opening pattern for exposing the FET formation region **1** over the substrate **211** is formed on the substrate **211** by lithography. Then, RIE etching is performed with respect to the third and second protective insulating films **216** and **213** by using CF_4 as an etchant and using the sixth resist film **256** as a mask, thereby exposing the first protective insulating film **212** through the FET formation region **1** of the sixth resist film **256**.

Next, as shown in FIG. **12D**, the sixth resist film **256** is removed and then a seventh resist film **257** having opening patterns for exposing the source/drain formation regions of the FET formation region **1** is formed on the substrate **211** by lithography. Subsequently, etching is performed with respect to the first protective insulating film **212** by using hydrogen fluoride and using the formed seventh resist film **257** as a mask, thereby exposing the source/drain formation regions of the top surface of the substrate **211**.

Next, a source/drain-electrode forming film composed of a multilayer structure of AuGe with a thickness of about 50 nm, Ni with a thickness of about 50 nm, and Au with a thickness of about 1000 nm is deposited entirely over the seventh resist film **257** including the opening patterns. Then,

32

the seventh resist film **257** is lifted off, whereby source/drain electrodes **219** are formed from the electrode forming film. Thereafter, a heat treatment is performed by raising the substrate temperature to about 400 ℃, thereby

5 alloying the source/drain regions **219** and an upper portion of the substrate **211**. Then, an eighth resist film **258** having an opening pattern for exposing the gate formation region in the FET formation region **1** is formed on the substrate **211** by lithography. Subsequently, recess etching using a phosphoric

10 acid as an etchant is performed with respect to the upper portion of the substrate **211** by using the formed eighth resist film **258** and the first protective insulating film **212** as a mask, thereby providing the state shown in FIG. **13A**.

Next, as shown in FIG. **13B**, a gate-electrode forming

15 film composed of a multilayer structure of Ti with a thickness of about 500 nm, Al with a thickness of about 5000 nm, and Ti with a thickness of about 500 nm is formed entirely over the eight resist film **258** including the opening pattern by vapor deposition. Then, the eighth resist film

20 **258** is lifted off, whereby a gate electrode **220** is formed from the electrode forming film. Thereafter, a fourth protective insulating film **221** composed of SiN is deposited by CVD over the entire surface of the substrate **211**.

Next, as shown in FIG. **13C**, a ninth resist film **259**

25 having opening patterns for exposing the respective portions

33

of the FET formation region 1 located over the source/drain

electrodes 219 and over the gate electrode 220 and exposing

the portion of the line formation region 2 located over the

first layer 218 of the linear conductor layer is formed.

5   Then, RIE etching is performed with respect to the fourth

protective insulating film 221 by using CF_4 and using the

ninth resist film 259 as a mask, thereby exposing each of the

electrodes 219 and 220 in the FET formation region 1 and

exposing the first layer 218 in the line formation region 2.

10   Next, as shown in FIG. 14A, the ninth resist film 259

is removed and then a multilevel layer 222A composed of Ti

with a thickness of about 0.05 μm and Au with a thickness of

about 0.15 μ m is formed over the entire surface of the

substrate 211 by vapor deposition. The multilevel layer 222A

15   serves as the layer 222A forming the second layer of the

linear conductor layer in the line formation region 2.

          Next, as shown in FIG. 14B, a tenth resist film 260

having opening patterns corresponding to the respective

portions of the FET formation region 1 located over the

20   source/drain regions 219 and over the gate electrode 220 and

corresponding to an area including the portion of the line

formation region 2 located over the first layer 218 of the

linear conductor layer is formed by lithography. The opening

patterns are connected to the microstrip line in the FET

25   formation region 1, while determining the wider portion of

the linear conductor layer having a width of about 5 μm in the line formation region **2**. Subsequently, an Au layer **223** with a thickness of 3 μm is formed by plating in each of the opening patterns.

5   Next, as shown in FIG. **14C**, the tenth resist film **260** is removed and then an unwanted portion of the Ti/Au multilevel layer **222A** is removed by using a KI etchant and hydrogen fluoride, whereby a wider portion **225b** of the linear conductor layer including the second layer **222** and the Au

10   layer **223** is formed in the line formation region **2**. From the wider portion **225b** and a narrower portion **225a**, a microstrip line **225** having a T-shaped cross-sectional configuration is formed.

Each of the microstrip line **155** and the spiral inductor

15   **156** may also be composed of a material other than Au, such as Ag or Cu.

Although the third embodiment has used the FET as an example of the active element, the active element may be a diode or a bipolar transistor such as HBT. Although GaAs has

20   been used in the substrate, silicon (Si) may also be used instead.

If an epitaxial layer using GaAs in the substrate and containing the active layer of the FET is structured as mentioned in the third embodiment, there can be adopted the

25   following structure which is advantageous in terms of

35

characteristics. Since the buffer layer composed of AlGaAs or InGaP provided between the substrate and the graded buffer layer presents excellent lattice matching with GaAs, the film thickness thereof can be increased relatively. This prevents fluorine atoms which are contained in the substrate during the formation thereof and undesired because of their possibility to cause a kink from being diffused from the substrate or buffer layer side toward the graded buffer layer side and to the channel layer side.

It is also possible to form the microstrip line according to the present embodiment on a substrate made of glass or quartz on which an active element cannot be formed and mount, by flip-chip bonding, an active element prepared separately on the substrate formed with the microstrip line.

Although the space between the wider portion **225b** of the linear conductor layer 225 and the dielectric layer **217** is filled with the fourth protective insulating film **222** composed of SiN in the present embodiment, the space may be filled preferably with a material having a lower dielectric constant such as an inorganic thin film composed of, e.g., SiO_2 or with an organic thin film composed of BCB, Duroid·, or the like.

Since the perimeter of a cross section of the microstrip line taken in a direction perpendicular to the direction in which the microstrip line extends is increased

36

according to the present embodiment, the conductor loss can significantly be reduced particularly in the frequency regions of micro waves and millimeter waves in which the conductor skin effect is dominant and the perimeter of the

5 line greatly affects the conductor loss.

By using Cu or Ag as a primary material of the microstrip line, the conductor loss can further be reduced.

A description will be given to the effect of using a high dielectric material such as STO as the dielectric

10 material used in the microstrip line. The wavelength of an electromagnetic wave propagating through the dielectric material is proportional to $1/\sqrt{\varepsilon}$. Since the dielectric constant of STO is about 200, which is more than ten times the dielectric constant of GaAs which is 12.9, the wavelength

15 of the electromagnetic wave propagating along the microstrip line becomes about a quarter or less of that of an electromagnetic wave propagating along a microstrip line using GaAs. If the microstrip line using STO as a dielectric material according to the present embodiment is used,

20 sufficient integration is achievable by folding the line into a meander configuration since the $\lambda/4$ wavelength becomes 1.6 mm at a frequency of 5 GHz. This allows impedance conversion using an on-chip $\lambda/4$ line as in the present embodiment, which is extremely effective in a matching circuit used for a

25 high-power MMIC.

If the microstrip line of the present embodiment is applied to an MMIC operating in the frequency region of quasi-millimeter wavers, $\lambda/4$ is reduced to about 300 μm, which allows a significant reduction in the area of a matching circuit using a distributed constant. Since the chip size can thus be reduced in the frequency region of each of micro waves and millimeter waves, there is achieved a remarkable effect of reducing the cost of an MMIC operating in the frequency region of millimeter waves, which is particularly high in cost.

Since a conventional via providing a connection between the linear conductor layer and the ground electrode has a connection length (hole length) of about 40 μm to 100 μm, the influence of the impedance thereof cannot be ignored particularly in the frequency region of millimeter waves. However, since a hole length of about 0.5 μm can be achieved in the microstrip line according to the present embodiment, there can be obtained an ideal short having an electrical length of 0 even in the high frequency region of several hundreds of gigahertz.